

Designer: Spreafico Design - Italy



WF 4 - DF 4 - ES 5



MINI 4 - DTR4 A/V



| | ECHO 4000 CV | ECHO 5000 CV | ECHO 6000 CV | ECHO 7000 CC/CV |
|---------------------------|--------------|--------------|--------------|-----------------|
| 3~ V 50/60 Hz | 230/400 | 230/400 | 230/400 | 230/400 |
| KVA | 20,1 | 29,2 | 40,0 | 46,0 |
| A | 45/25 | 63/35 | 80/45 | 85/50 |
| P_{FACTOR} | 0,92 | 0,91 | 0,90 | 0,88 |
| cos φ | 0,95 | 0,94 | 0,92 | 0,90 |
| η_{MAX} | 0,76 | 0,75 | 0,73 | 0,76 |
| V | 16,5 - 44 | 17 - 51 | 17,5 - 58 | 22 - 56 |
| I₂ | 25 - 400 | 25 - 500 | 30 - 600 | 25 - 700 |
| A 100% | 230 | 310 | 390 | 460 |
| A 60% | 310 | 400 | 500 | 600 |
| A 40% | 400 | 500 | 600 | 700 |
| mm | 0,6 - 1,6 | 0,6 - 1,6 | 0,8 - 2,0 | 0,8 - 2,4 |
| IP.. | 23 S | 23 S | 23 S | 23 S |
| mm | 1060 | 1060 | 1060 | 1060 |
| mm | 600 | 600 | 600 | 600 |
| mm | 780 | 780 | 780 | 780 |
| Kg | 104 | 116 | 146 | 180 |
| ES 5 | • | • | • | --- |
| --- | --- | --- | --- | • |
| --- | --- | --- | --- | • |



WF 4



DF 4



ES 5



DTR4 A/V



MINI 4



IR 14

